

Multi-turn actuator			Motor				Fuse <sup>1)</sup>
Type	Output speed [rpm]	Max. torque [Nm]	Motor type	Consumed nominal power <sup>2)</sup> P <sub>IN</sub> [kW]	Nominal current <sup>3)</sup> I <sub>N</sub> [A]	Max. current <sup>4)</sup> I <sub>max</sub> [A]	Blow characteristics: Time-delay (gG) [A]
SARVEx 07.2	6 – 60	30	ADYR063-4-0,10	0.5	2.0	2.7	6
	12 – 108		ADYR063-2-0,20	0.5	2.1	4.0	6
	24 – 216	25	ADYR063-2-0,30	0.6	2.6	5.6	10
SARVEx 07.6	6 – 60	60	ADYR063-4-0,20	0.7	2.8	4.0	6
	12 – 108		ADYR063-2-0,40	0.9	3.4	6.2	10
	24 – 216	50	ADYR063-2-0,50	1.0	4.0	6.8	10
SARVEx 10.2	6 – 60	120	ADYR071-4-0,40	1.1	4.1	6.9	10
	12 – 108		ADYR071-2-0,70	1.4	5.7	9.8	16
	24 – 216	100	ADYR071-2-1,00	1.9	6.0	12	16
SARVEx 14.2	6 – 60	250	ADYR090-4-0,75	1.5	4.8	7.8	10
	12 – 108		ADYR090-2-1,40	2.5	7.9	14	16
	24 – 216	200	ADYR090-2-1,80	3.2	10	19	25
SARVEx 14.6	6 – 60	500	ADYR090-4-1,60	3.0	9.4	14	16

**Notes on table**

1) Protection on site	For short-circuit protection of the actuator, fuses have to be provided by the customer. The actuators are suitable for use in current circuits with a maximum short-circuit 1-phase AC current value of 5,000 A root-mean-square (R.M.S). The output data of the fuses to be provided on site must not exceed the following values: 32 A/600 V at a maximum mains mains short circuit current of 5,000 A AC.
2) Consumed nominal power P <sub>IN</sub>	Mains power consumption for 230 V rated voltage V at multi-turn actuator run torque (approx. 35 % of the maximum torque) and maximum output speed.
3) Nominal current I <sub>N</sub>	Mains current consumption for 230 V rated voltage V at multi-turn actuator run torque (approx. 35 % of the maximum torque) and maximum output speed.
4) Max. current I <sub>max</sub>	Mains current consumption for 230 V rated voltage at maximum torque and approx. 50 % output speed. Starting current I <sub>A</sub> ≤ I <sub>max</sub>

**Notes on installation and sizing**

Electrical data	Current and power data are approximate. Due to usual manufacturing tolerances, there may be deviations from the values given.
Rated voltage	Mains voltage for defining current and power data
Motor operation	On the basis of the supplied 1-phase or 3-phase AC mains voltage, the frequency converter generates a variable 3-phase AC voltage, adjustable in terms of frequency and amplitude. Motor speed and thus actuator speed is internally set via the frequency.
Motor protection	To protect against overheating, PTC thermistors are embedded in the motor windings. Evaluation of PTC thermistors is integrated in the ACVExC controls.
Mains voltage, mains frequency	Permissible variation of mains voltage: ±10 % Permissible variation of mains frequency: ±5 %