

## Electrical data Part-turn actuators for modulating duty

## Intermittent duty S4 - 25 %, Mains voltage 110 – 120 V/50 – 60 Hz 1-phase AC current

## General information

Part-turn actuators of the SQRV .2 type range with variable operating times. AUMA actuator controls of ACV .2 type are required to change the operating time.

Part-turn actuator			Current and power data <sup>1)</sup>				Fuse <sup>2)</sup>
Type	Operating time for 90° [s]	Max. torque [Nm]	Motor type	Consumed rated power <sup>3)</sup> P <sub>IN</sub> [kW]	Nominal current <sup>4)</sup> I <sub>N</sub> [A]	Max. current <sup>5)</sup> I <sub>max</sub> [A]	Blow characteristics: Time-delay (gG) [A]
SQRV 05.2	4 – 28	150	VSVR063-2-0,06	0.22	2.9	2.9	6.0
	12 – 120		VSVR063-4-0,02	0.10	1.3	2.0	6.0
SQRV 07.2	4 – 28	300	VSVR063-2-0,12	0.32	3.8	6.4	6.0
	12 – 120		SSVR063-4-0,03	0.15	1.9	2.9	6.0
SQRV 10.2	12 – 120	600	SSVR063-4-0,06	0.19	2.3	4.3	6.0
SQRV 12.2	24 – 240	1,200	SSVR063-4-0,06	0.19	2.3	4.3	6.0
SQRV 14.2	40 – 360	2,400	SSVR063-2-0,10	0.20	2.6	4.2	6.0

1) Motor with ACV actuator controls

2) For short-circuit protection of the actuator, fuses have to be provided by the customer. The actuator are suitable for use in current circuits with a maximum short-circuit AC current value of 5,000 A root-mean-square (R.M.S). The output data of the fuses to be provided on site must not exceed the following values: 32 A/600 V at a maximum mains short circuit current of 5,000 A AC.

3) Mains power consumption for 115 V rated voltage V at part-turn actuator run torque (approx. 35 % of the maximum torque) and maximum operating time.

4) Mains current consumption for 115 V rated voltage V at part-turn actuator run torque (approx. 35 % of the maximum torque) and maximum operating time.

5) Mains current consumption for 115 V rated voltage at maximum torque and approx. 50 % operating time. Starting current  $I_A \leq I_{max}$ .

## Notes on installation and sizing

Electrical data	Current and power data are approximate. Due to usual manufacturing tolerances, there may be deviations from the values given.
Rated voltage	Mains voltage for defining current and power data
Motor operation	On the basis of the supplied 1-phase or 3-phase AC mains voltage, the frequency converter generates a variable 3-phase AC voltage, adjustable in terms of frequency and amplitude. Motor speed and thus actuator operating time is internally set via the frequency.
Motor protection	To protect against overheating, thermoswitches or PTC thermistors are embedded in the motor windings. Evaluation of thermoswitches or PTC thermistors is integrated in the ACV actuator controls.
Mains voltage, mains frequency	Permissible variation of mains voltage: $\pm 10$ % Permissible variation of mains frequency: $\pm 5$ %